

JDYX2.E486200 - FUSES, SUPPLEMENTAL - COMPONENT

Fuses, Supplemental - Component

See General Information for Fuses, Supplemental - Component

SHENZHEN JDT FUSE INDUSTRIAL CO LTD

ROOM 02, 3F, BLDG Y1, BANTIAN CREATIVE PARK
5 YAYUAN ROAD
BANTIAN, LONGGANG DISTRICT
SHENZHEN, GUANDONG 518000 CHINA

E486200

Supplemental fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
JFC5Fxxxxx	5.2 x 20 (0.20 x 0.79)	0.2 - 0.25	125Vac	10000
		0.3 - 2	125Vac	10000
		2.5 - 10	125Vac	10000
		0.2 - 0.25	250Vac	35
		0.3 - 1	250Vac	35
		1.25 - 2	250Vac	100
		2.5 - 3.15	250Vac	100
		4 - 10	250Vac	200
JFC5Txxxxx	5.2 x 20 (0.20 x 0.79)	0.2 - 0.25	125Vac	10000
		0.3 - 2	125Vac	10000
		2.5 - 10	125Vac	10000
		0.2 - 0.25	250Vac	35
		0.3 - 1	250Vac	35
		1.25 - 2	250Vac	100
		2.5 - 3.15	250Vac	100
		4 - 10	250Vac	200
JFG5Fxxxxx	5.2 x 20 (0.20 x 0.79)	0.2 - 0.25	125Vac	10000
		0.3 - 2	125Vac	10000

		2.5 - 10	125Vac	10000
		0.2 - 0.25	250Vac	35
		0.3 - 1	250Vac	35
		1.25 - 2	250Vac	100
		2.5 - 3.15	250Vac	100
		4 - 10	250Vac	200
JFG5Txxxxx	5.2 x 20 (0.20 x 0.79)	0.2 - 0.25	125Vac	10000
		0.3 - 2	125Vac	10000
		2.5 - 10	125Vac	10000
		0.2 - 0.25	250Vac	35
		0.3 - 1	250Vac	35
		1.25 - 2	250Vac	100
		2.5 - 3.15	250Vac	100
		4 - 10	250Vac	200

Supplemental fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
JFPxxxxFL-350V	4 x 11 (0.16 x 0.43)	0.1 - 3	350Vac	100
		3.15 - 10	350Vac	100
JFPxxxxTL-350V	4 x 11 (0.16 x 0.43)	0.1 - 3	350Vac	100
		3.15 - 10	350Vac	100

Supplemental micro fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
JFC1206-xxxxAS (#)	3.2 x 1.6 x 0.65 (0.13 x 0.06 x 0.03)	0.1 - 30	24Vdc	300
		0.1 - 7	32Vdc	50
		0.1 - 5	72Vdc	50
		0.1 - 3	125Vdc	50
		0.1 - 5	125Vac	50
		0.1 - 5	63Vdc	50
JFC1206-xxxxFS (#)	3.2 x 1.6 x 0.65 (0.13 x 0.06 x 0.03)	0.1 - 30	24Vdc	300

		0.1 - 7	32Vdc	50
		0.1 - 5	72Vdc	50
		0.1 - 3	125Vdc	50
		0.1 - 5	125Vac	50
		0.1 - 5	63Vdc	50
JFC1206-xxxxGS (#)	3.2 x 1.6 x 0.65 (0.13 x 0.06 x 0.03)	0.1 - 30	24Vdc	300
		0.1 - 7	32Vdc	50
		0.1 - 5	72Vdc	50
		0.1 - 3	125Vdc	50
		0.1 - 5	125Vac	50
		0.1 - 5	63Vdc	50
JFC1206-xxxxHFS (#)	3.2 x 1.6 x 0.65 (0.13 x 0.06 x 0.03)	0.1 - 30	24Vdc	300
		0.1 - 7	32Vdc	50
		0.1 - 5	72Vdc	50
		0.1 - 3	125Vdc	50
		0.1 - 5	125Vac	50
		0.1 - 5	63Vdc	50
JFC1206-xxxxKS (#)	3.2 x 1.6 x 0.65 (0.13 x 0.06 x 0.03)	0.1 - 30	24Vdc	300
		0.1 - 7	32Vdc	50
		0.1 - 5	72Vdc	50
		0.1 - 3	125Vdc	50
		0.1 - 5	125Vac	50
		0.1 - 5	63Vdc	50
JFC1206-xxxxLS (#)	3.2 x 1.6 x 0.65 (0.13 x 0.06 x 0.03)	0.1 - 30	24Vdc	300
		0.1 - 7	32Vdc	50
		0.1 - 5	72Vdc	50
		0.1 - 3	125Vdc	50
		0.1 - 5	125Vac	50
		0.1 - 5	63Vdc	50
JFC1206-xxxxTS (#)	3.2 x 1.6 x 0.65 (0.13 x 0.06 x 0.03)	0.1 - 30	24Vdc	300

		0.1 - 7	32Vdc	50
		0.1 - 5	72Vdc	50
		0.1 - 3	125Vdc	50
		0.1 - 5	125Vac	50
		0.1 - 5	63Vdc	50
JFPxxxxFL	3 x 7.2 (0.12 x 0.28)	0.1 - 3	125Vac	30
		0.1 - 3	250Vac	30
		3.15 - 6.3	125Vac	30
		3.15 - 6.3	250Vac	30
JFPxxxxTL	3 x 7.2 (0.12 x 0.28)	0.1 - 3	125Vac	30
		0.1 - 3	250Vac	30
		3.15 - 6.3	125Vac	30
		3.15 - 6.3	250Vac	30

Supplemental micro fuses: filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
JFSXXXXFR	8.4 x 7.7 x 4 (0.33 x 0.30 x 0.16)	0.1 - 6.3	250Vac	50
		0.1 - 6.3	350Vac	50
JFSXXXXTR	8.4 x 7.7 x 4 (0.33 x 0.30 x 0.16)	0.1 - 6.3	250Vac	50
		0.1 - 6.3	350Vac	50

Supplemental micro fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
JFG3Fxxxxx	3.6 x 10 (0.14 x 0.39)	0.25 - 0.5	125Vac	50
		0.25 - 0.5	250Vac	50
		0.63 - 1.6	125Vac	50
		0.63 - 1.6	250Vac	50
		2 - 5	125Vac	50
		2 - 5	250Vac	50
JFG3Txxxxx	3.6 x 10 (0.14 x 0.39)	0.25 - 0.4	125Vac	50

		0.25 - 0.4	250Vac	50
		0.5 - 5	125Vac	50
		0.5 - 5	250Vac	50
JFG6Fxxxxx	8.3 x 5 x 3.9 (0.33 x 0.20 x 0.15)	0.05 - 10	250Vac	50
		0.05 - 10	300Vac	50
		0.05 - 10	250Vdc	50
JFG6Txxxxx	8.3 x 5 x 3.9 (0.33 x 0.20 x 0.15)	0.05 - 10	250Vac	50
		0.05 - 10	300Vac	50
		0.05 - 10	250Vdc	50
JFSxxxxFR-300V	8.4 x 4 x 8.2 (0.33 x 0.16 x 0.32)	0.05 - 6.3	300Vac	50
JFSxxxxFR-350V	8.4 x 4 x 8.2 (0.33 x 0.16 x 0.32)	0.05 - 6.3	350Vac	50
JFSxxxxTR-300V	8.4 x 4 x 8.2 (0.33 x 0.16 x 0.32)	0.05 - 6.3	300Vac	50
JFSxxxxTR-350V	8.4 x 4 x 8.2 (0.33 x 0.16 x 0.32)	0.05 - 6.3	350Vac	50

Supplemental micro fuses: surface mount

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
JFC0603-xxxxAS (#)	1.6 x 0.81 x 0.65 (0.06 x 0.03 x 0.03)	0.1 - 1.5	63Vdc	50
		0.1 - 8	32Vdc	50
JFC0603-xxxxFS (#)	1.6 x 0.81 x 0.65 (0.06 x 0.03 x 0.03)	0.1 - 1.5	63Vdc	50
		0.1 - 8	32Vdc	50
JFC0603-xxxxGS (#)	1.6 x 0.81 x 0.65 (0.06 x 0.03 x 0.03)	0.1 - 1.5	63Vdc	50
		0.1 - 8	32Vdc	50
JFC0603-xxxxHFS (#)	1.6 x 0.81 x 0.65 (0.06 x 0.03 x 0.03)	0.1 - 1.5	63Vdc	50
		0.1 - 8	32Vdc	50
JFC0603-xxxxLS (#)	1.6 x 0.81 x 0.65 (0.06 x 0.03 x 0.03)	0.1 - 1.5	63Vdc	50
		0.1 - 8	32Vdc	50
JFC0603-xxxxTS (#)	1.6 x 0.81 x 0.65 (0.06 x 0.03 x 0.03)	0.1 - 1.5	63Vdc	50

		0.1 - 8	32Vdc	50
JFC2410-xxxxFS-125V	6.1 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.05 - 15	125Vac	200
JFC2410-xxxxFS-250V	6.1 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.05 - 7	250Vac	50
JFC2410-xxxxFS-300V	6.1 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.05 - 7	300Vac	50
JFC2410-xxxxTS-125V	6.1 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.05 - 15	125Vac	200
JFC2410-xxxxTS-250V	6.1 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.05 - 7	250Vac	50
JFC2410-xxxxTS-300V	6.1 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.05 - 7	300Vac	50

- xxx represents 4-digit ampere code. The 2nd, 3rd and 4th digit represent the tenth-digit, hundredth-digit and thousandth-digit of the figure, the 1st digit indicates that 10 is to the power of this digit. (Example 0500A= $0.500 \times 10^0 = 0.5A$; 1315A= $0.315 \times 10^1 = 3.15A$; 2150A= $0.150 \times 10^2 = 15A$).

Marking: Company name and model designation.

Last Updated on 2019-01-09

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2019 UL LLC"